

850 Purchase Order

Version: 004010 X12

Author:	DOT FOODS, INC.
Publication:	March 28, 2006

850 Purchase Order

Functional Group=PO

This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BEG	Beginning Segment for Purchase Order	M	1			Must use
150	DTM	Date/Time Reference	O	10			Used
240	TD5	Carrier Details (Routing Sequence/Transit Time)	O	12			Used

LOOP ID - N9

1000

295	N9	Reference Identification	O	1			Used
300	MSG	Message Text	O	1000			Used

LOOP ID - N1

200

310	N1	Name	O	1			Used
330	N3	Address Information	O	2			Used
340	N4	Geographic Location	O	>1			Used
310	N1	Name	O	1			Used
330	N3	Address Information	O	2			Used
340	N4	Geographic Location	O	>1			Used
310	N1	Name	O	1			Used
330	N3	Address Information	O	2			Used
340	N4	Geographic Location	O	>1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
------------	-----------	---------------------	------------	----------------	---------------	--------------	--------------

LOOP ID - PO1

100000

N2/010L

010	PO1	Baseline Item Data	M	1		N2/010	Must use
-----	-----	--------------------	---	---	--	--------	----------

LOOP ID - PID

1000

050	PID	Product/Item Description	O	1			Used
-----	-----	--------------------------	---	---	--	--	------

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
------------	-----------	---------------------	------------	----------------	---------------	--------------	--------------

LOOP ID - CTT

1

N3/010L

010	CTT	Transaction Totals	O	1		N3/010	Used
030	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
------------	-----------	---------------------	------------	----------------	---------------	--------------	--------------

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

2/010L PO102 is required.

2/010 PO102 is required.

3/010L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/010 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use	1
<p>Description: Code to identify the type of information in the Authorization Information</p> <p>Code Name 00 No Authorization Information Present (No Meaningful Information in I02)</p>							
ISA02	I02	Authorization Information	M	AN	10/10	Must use	1
<p>Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)</p>							
ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use	1
<p>Description: Code to identify the type of information in the Security Information</p> <p>Code Name 00 No Security Information Present (No Meaningful Information in I04)</p>							
ISA04	I04	Security Information	M	AN	10/10	Must use	1
<p>Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)</p>							
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use	1
<p>Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element being qualified</p> <p>Code Name 08 UCC EDI Communications ID (Comm ID)</p>							
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use	1
<p>Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element</p> <p>Dot Foods: 9288030000</p>							
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use	1
<p>Description: Qualifier to designate the system/method of code structure used to designate the sender or receiver ID element</p>							

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
		being qualified					
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use	1
		Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them					
ISA09	I08	Interchange Date	M	DT	6/6	Must use	1
		Description: Date of the interchange					
ISA10	I09	Interchange Time	M	TM	4/4	Must use	1
		Description: Time of the interchange					
ISA11	I10	Interchange Control Standards Identifier	M	ID	1/1	Must use	1
		Description: Code to identify the agency responsible for the control standard used by the message that is enclosed by the interchange header and trailer All valid standard codes are used.					
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use	1
		Description: Code specifying the version number of the interchange control segments Code Name 00401 Draft Standards for Trial Use Approved for Publication by ASC X12 Procedures Review Board through October 1997					
ISA13	I12	Interchange Control Number	M	N0	9/9	Must use	1
		Description: A control number assigned by the interchange sender					
ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use	1
		Description: Code sent by the sender to request an interchange acknowledgment (TA1) Code Name 0 No Acknowledgment Requested					
ISA15	I14	Usage Indicator	M	ID	1/1	Must use	1
		Description: Code to indicate whether data enclosed by this interchange envelope is test, production or information Code Name P Production Data					
ISA16	I15	Component Element Separator	M		1/1	Must use	1
		Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator					

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use	1
		Description: Code identifying a group of application related transaction sets					
		Code Name					
		PO Purchase Order (850)					
GS02	142	Application Sender's Code	M	AN	2/15	Must use	1
		Description: Code identifying party sending transmission; codes agreed to by trading partners					
		Dot Foods: 9288030000					
GS03	124	Application Receiver's Code	M	AN	2/15	Must use	1
		Description: Code identifying party receiving transmission; codes agreed to by trading partners					
GS04	373	Date	M	DT	8/8	Must use	1
		Description: Date expressed as CCYYMMDD					
GS05	337	Time	M	TM	4/8	Must use	1
		Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)					
GS06	28	Group Control Number	M	N0	1/9	Must use	1
		Description: Assigned number originated and maintained by the sender					
GS07	455	Responsible Agency Code	M	ID	1/2	Must use	1
		Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480					
		Code Name					
		X Accredited Standards Committee X12					
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use	1
		Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including					

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
		the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed					
		<u>Code</u> <u>Name</u>					
		004010 Draft Standards Approved for Publication by ASC X12 Procedures Review Board through October 1997					

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use	1
		Description: Code uniquely identifying a Transaction Set					
		Code Name					
		850 Purchase Order					
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use	1
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set					

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BEG Beginning Segment for Purchase Order

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
BEG01	353	Transaction Set Purpose Code	M	ID	2/2	Must use	1
		Description: Code identifying purpose of transaction set					
		Code Name					
		00 Original					
BEG02	92	Purchase Order Type Code	M	ID	2/2	Must use	1
		Description: Code specifying the type of Purchase Order					
		Code Name					
		NE New Order					
BEG03	324	Purchase Order Number	M	AN	1/22	Must use	1
		Description: Identifying number for Purchase Order assigned by the orderer/purchaser					
BEG05	373	Date	M	DT	8/8	Must use	1
		Description: Date expressed as CCYYMMDD					

Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

DTM Date/Time Reference

Pos: 150	Max: 10
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use	1
		Description: Code specifying type of date or time, or both date and time					
		Code Name					
		002				Delivery Requested	
		118				Requested Pick-up	
DTM02	373	Date	X	DT	8/8	Used	1
		Description: Date expressed as CCYYMMDD					

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

TD5 Carrier Details (Routing Sequence/Transit Time)

Pos: 240 Max: 12

Heading - Optional

Loop: N/A

Elements: 1

User Option (Usage): Used

To specify the carrier and sequence of routing and provide transit time information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
TD504	91	Transportation Method/Type Code	X	ID	1/2	Used	1

Description: Code specifying the method or type of transportation for the shipment

Code Name

H	Customer Pickup
M	Motor (Common Carrier)

Syntax Rules:

1. R0204050612 - At least one of TD502, TD504, TD505, TD506 or TD512 is required.
2. C0203 - If TD502 is present, then TD503 is required.
3. C0708 - If TD507 is present, then TD508 is required.
4. C1011 - If TD510 is present, then TD511 is required.
5. C1312 - If TD513 is present, then TD512 is required.
6. C1413 - If TD514 is present, then TD513 is required.
7. C1512 - If TD515 is present, then TD512 is required.

Semantics:

1. TD515 is the country where the service is to be performed.

Comments:

1. When specifying a routing sequence to be used for the shipment movement in lieu of specifying each carrier within the movement, use TD502 to identify the party responsible for defining the routing sequence, and use TD503 to identify the actual routing sequence, specified by the party identified in TD502.

N9 Reference Identification

Pos: 295	Max: 1
Heading - Optional	
Loop: N9	Elements: 2

User Option (Usage): Used

To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use	1
		Description: Code qualifying the Reference Identification					
		Code Name					
		PO Purchase Order Number					
N902	127	Reference Identification	X	AN	1/30	Used	1
		Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier					

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MSG Message Text

Pos: 300	Max: 1000
Heading - Optional	
Loop: N9	Elements: 1

User Option (Usage): Used

To provide a free-form format that allows the transmission of text information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
MSG01	933	Free-Form Message Text	M	AN	1/264	Must use	1

Description: Free-form message text

Syntax Rules:

1. C0302 - If MSG03 is present, then MSG02 is required.

Semantics:

1. MSG03 is the number of lines to advance before printing.

Comments:

1. MSG02 is not related to the specific characteristics of a printer, but identifies top of page, advance a line, etc.
2. If MSG02 is "AA - Advance the specified number of lines before print" then MSG03 is required.

N1 Name

Pos: 310	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N101	98	Entity Identifier Code Description: Code identifying an organizational entity, a physical location, property or an individual Code Name SF Ship From	M	ID	2/3	Must use	1
N102	93	Name Description: Free-form name	X	AN	1/60	Used	1
N103	66	Identification Code Qualifier Description: Code designating the system/method of code structure used for Identification Code (67) Code Name 9 D-U-N-S+4, D-U-N-S Number with Four Character Suffix	X	ID	1/2	Used	1
N104	67	Identification Code Description: Code identifying a party or other code	X	AN	2/80	Used	1

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 330	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N301	166	Address Information	M	AN	1/55	Must use	1
		Description: Address information					
N302	166	Address Information	O	AN	1/55	Used	1
		Description: Address information					

N4 Geographic Location

Pos: 340	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N401	19	City Name	O	AN	2/30	Used	1
		Description: Free-form text for city name					
N402	156	State or Province Code	O	ID	2/2	Used	1
		Description: Code (Standard State/Province) as defined by appropriate government agency					
N403	116	Postal Code	O	ID	3/15	Used	1
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)					

Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

N1 Name

Pos: 310 Max: 1

Heading - Optional

Loop: N1

Elements: 4

User Option (Usage): Used

To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N101	98	Entity Identifier Code Description: Code identifying an organizational entity, a physical location, property or an individual Code Name BT Bill-to-Party	M	ID	2/3	Must use	1
N102	93	Name Description: Free-form name	X	AN	1/60	Used	1
N103	66	Identification Code Qualifier Description: Code designating the system/method of code structure used for Identification Code (67) Code Name 9 D-U-N-S+4, D-U-N-S Number with Four Character Suffix	X	ID	1/2	Used	1
N104	67	Identification Code Description: Code identifying a party or other code Dot Foods: 0256712560000	X	AN	2/80	Used	1

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 330	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N301	166	Address Information	M	AN	1/55	Must use	1
		Description: Address information					
N302	166	Address Information	O	AN	1/55	Used	1
		Description: Address information					

N4 Geographic Location

Pos: 340	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N401	19	City Name	O	AN	2/30	Used	1
		Description: Free-form text for city name					
N402	156	State or Province Code	O	ID	2/2	Used	1
		Description: Code (Standard State/Province) as defined by appropriate government agency					
N403	116	Postal Code	O	ID	3/15	Used	1
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)					

Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

N1 Name

Pos: 310	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use	1
		Description: Code identifying an organizational entity, a physical location, property or an individual					
		Code Name					
		ST Ship To					
N102	93	Name	X	AN	1/60	Used	1
		Description: Free-form name					
N103	66	Identification Code Qualifier	X	ID	1/2	Used	1
		Description: Code designating the system/method of code structure used for Identification Code (67)					
		Code Name					
		9 D-U-N-S+4, D-U-N-S Number with Four Character Suffix					
N104	67	Identification Code	X	AN	2/80	Used	1
		Description: Code identifying a party or other code					

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Address Information

Pos: 330	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N301	166	Address Information	M	AN	1/55	Must use	1
		Description: Address information					
N302	166	Address Information	O	AN	1/55	Used	1
		Description: Address information					

N4 Geographic Location

Pos: 340	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
N401	19	City Name	O	AN	2/30	Used	1
		Description: Free-form text for city name					
N402	156	State or Province Code	O	ID	2/2	Used	1
		Description: Code (Standard State/Province) as defined by appropriate government agency					
N403	116	Postal Code	O	ID	3/15	Used	1
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)					

Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

PO1 Baseline Item Data

Pos: 010	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 11

User Option (Usage): Must use

To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
PO102	330	Quantity Ordered	X	R	1/15	Used	1
		Description: Quantity ordered					
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Used	1
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken					
		Code Name					
		CA Case					
		EA Each					
PO104	212	Unit Price	X	R	1/17	Used	1
		Description: Price per unit of product, service, commodity, etc.					
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Used	1
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)					
		Code Name					
		UK U.P.C./EAN Shipping Container Code (1-2-5-5-1)					
PO107	234	Product/Service ID	X	AN	1/48	Used	1
		Description: Identifying number for a product or service					
		Dot Foods: 14 digit case GTIN (SCC-14)					
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used	1
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)					
		Code Name					
		UA U.P.C./EAN Case Code (2-5-5)					
PO109	234	Product/Service ID	X	AN	1/48	Used	1
		Description: Identifying number for a product or service					
		Dot Foods: 12 digit case UPC					
PO110	235	Product/Service ID Qualifier	X	ID	2/2	Used	1
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)					

		<u>Code</u>	<u>Name</u>					
		MG	Manufacturer's Part Number					
PO111	234	Product/Service ID		X	AN	1/48	Used	1
		Description: Identifying number for a product or service						
		Dot Foods: <i>Manufacturer product number</i>						
PO112	235	Product/Service ID Qualifier		X	ID	2/2	Used	1
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
		<u>Code</u>	<u>Name</u>					
		PI	Purchaser's Item Code					
PO113	234	Product/Service ID		X	AN	1/48	Used	1
		Description: Identifying number for a product or service						
		Dot Foods: <i>Dot item number</i>						

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

PID Product/Item Description

Pos: 050	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Used

To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
PID01	349	Item Description Type	M	ID	1/1	Must use	1
		Description: Code indicating the format of a description					
		Code Name					
		F Free-form					
PID05	352	Description	X	AN	1/80	Used	1
		Description: A free-form description to clarify the related data elements and their content					

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

CTT Transaction Totals

Pos: 010	Max: 1
Summary - Optional	
Loop: CTT	Elements: 4

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use	1
		Description: Total number of line items in the transaction set					
CTT02	347	Hash Total	O	R	1/10	Used	1
		Description: Sum of values of the specified data element. All values in the data element will be summed without regard to decimal points (explicit or implicit) or signs. Truncation will occur on the left most digits if the sum is greater than the maximum size of the hash total of the data element. Example: -.0018 First occurrence of value being hashed. .18 Second occurrence of value being hashed. 1.8 Third occurrence of value being hashed. 18.01 Fourth occurrence of value being hashed. ----- 1855 Hash total prior to truncation. 855 Hash total after truncation to three-digit field.					
		Dot Foods: Total order quantity					
CTT03	81	Weight	X	R	1/10	Used	1
		Description: Numeric value of weight					
		Dot Foods: Total order weight					
CTT04	355	Unit or Basis for Measurement Code	X	ID	2/2	Used	1
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken					
		Code Name					
		LB Pound					

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
SE01	96	Number of Included Segments	M	NO	1/10	Must use	1
		Description: Total number of segments included in a transaction set including ST and SE segments					
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use	1
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set					

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
GE01	97	Number of Transaction Sets Included	M	NO	1/6	Must use	1
		Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element					
GE02	28	Group Control Number	M	NO	1/9	Must use	1
		Description: Assigned number originated and maintained by the sender					

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>	<u>Rep</u>
IEA01	I16	Number of Included Functional Groups	M	NO	1/5	Must use	1
		Description: A count of the number of functional groups included in an interchange					
IEA02	I12	Interchange Control Number	M	NO	9/9	Must use	1
		Description: A control number assigned by the interchange sender					